

The MARS GAMING's MK2 is a standard 104 keys layout illuminated gaming keyboard. It consists of six micro keys G1-G6, and a software allows macro setting and self-defined hot keys. It also includes nine multimedia keys and three self-defined function keys (M1/M2/M3). MAX memory space is 64KB and store 18 sets MACRO keys to the keyboard, so no need to set the profiles again when moving to another computer.

### Specification:

Connection: wired USB, cable length 180 cm

Interface: USB1.1 above

Input power: between 4.5V and 5.5V

Power: MAX 300MA

Macro Keys: 6

Glow function: all keys with lighting (laser with lighting)

Key lifetime: 10,000,000hr

Backlight color: blue, red, purple

Key structure design: crater structure design

Keyboard dimension: 505.\*211\*30.5MM

Weight: 843g

### Keyboard shortcuts:

FN+F1	Slow down key response time from 1ms to 8ms	FN+F7	Forward the Web page	FN+Scroll Lock	Exchange ASDW and Direction keys
FN+F2	Speed up key response time	FN+F8	Backward the Web page	FN+Pause Break	Backlight color effect switch
FN+F3	Slow down the polling rate (or report rate)	FN+F9	20%Backlight	FN+Print screen	Exit&Enter the game mode
FN+F4	Speed up the polling rate from 125Hz to 1000Hz	FN+F10	60%Backlight	FN+WIN	Exchange ASDW and Direction keys
FN+F5	Calculator	FN+F11	100%Backlight	M1-M3	3 kinds of profile setting
FN+F6	Refresh the Web page	FN+F12	Breathing backlight effect	G1-G6	macro definition key

**Note:** You will not be able to enter password to the internet banking when keyboard is in gaming mode, it is workable when keyboard is changed into the normal mode. (The windows key is available when keyboard in normal mode, but no any function in gaming mode)

**Note:** Please uninstall previous keyboard software (if any) from your PC, then double-click setup.exe to install MK2 software onto your PC.



Go to the Main screen after the software installation.



Key functions can be re-assigned simply by selecting a key (inverted to red color) and choose a key to replace its previous function. (multimedia keys and special function keys can not be re-assigned)



Go to MACRO SETTING



Click MACRO MANAGER and click NEW



Type in a new Macro name and click OK



Click Start Record and start inputing combination of keys. You can also set the number of Loop Times and choose to Record delays between key commands.



Any of the G1-G6 keys can be assigned as a Macro or a multimedia key.



Assigning the newly recorded Macro to any of the G1-G6 keys.



In the ADVANCED SETTING, you can set the POLLING RATE, KEY RESPONSE TIME, selecting the keyboard backlight LED color and the LIGHT INTENSITY.